

□□□□□□□□WK-618□



1.Max□□□□□129±5□□

2.Max□□□□□≥50dB

3.Harmonic□□□□□≤5%

4.Frequency□□□450□3500Hz

5.Input□□□≤30dB

6.Battery□AG13 OR A 675□□□□□

7.Working□□□D.C.1.5v

8.Working□□□≤4mA

9.Measurement□5.3 * 4.4 *1.0□□

10.Net□□□9□□□□□□□□

□□□□□