

NEW DIGITAL LIGHT LEVEL METER LX-1330B



1. 1 000 000 : 0-200 LUX

2,000 LUX
20,000 LUX
20 000 LUX

2. 0000 : 0 ~ 200 LUX : ± 3 %

201 ~ 2,000 LUX : ± 3 %
2,001 ~ 20,000 LUX : ± 4 %
20,001 ~ 200,000 LUX : ± 4 %

3. 0000 00 : 0.2 0 / 0

4. 0000 00 : 00 0000

5. 00 : 147 X 71 X 41mm (00 00)

6. 00 0000 00 : 4 X 2.5 X 1 (00)

7. 0 00000 00 : 0000 00 000000 00

8. 00 00 00 Footcandle 00 00

9. 0000 : + / - 2 %

10. 00 00 : + / - 0.1 % C

11. 00 00 : 32 ~ 104° F (0 ~ 40° C)

12. 3 1 / 2 0000 LCD

13. 00 00

14. 0000 00

15. 00 00 00

16. 00 00 00

17. 00 : 9V (6F22) × 1

18. 0000 00 : 200 00 00 (00)

19. 00 00 : 250g